

Low Voltage Track Cylinder

Model No. TL2001-BST/FR

Project Details

Job Name	
Location	
Type/Qty	
Contact Info	
Note	

Features

- Directional light source providing 225° vertical aiming capability with 335° horizontal rotation
- Dimmer compatible
- Re-lamps from the front
- Ceramic 12V AC MR16 base socket
- May be modified to fit other major brands
- I/P: AC 120V 60Hz 0.6A
- O/P: AC 12V 80W max. *
- * Our 80 watt rating is reserved for Trac-Tech low voltage cylinders built to the highest standards. Although rated for use with 50 watt bulbs, these heads feature top quality 80 watt electronic transformers to allow a longer, trouble-free life.
- Available Finishes: Black (BLK), Brushed Steel (BST)

SPECIFICATION

OAH (in.)	6.5
Overall Width (in.)	2.25
OA Depth (in.)	4
Bulb	MR16CG 12V
Max. wattage (W)	50
Number of Bulbs	1
Bulb included	No
Dimmable	Yes
Voltage	12V
Certifications and Listings	ETL Listed
Warranty	1 Year

LED Info



Description

Low voltage track head cylinder in a Brushed Steel finish with Frost Glass Face Ring for use with MR16CG 12V/50W Lamps

LINE DRAWING
CURRENTLY UNAVAILABLE



IMAGE COMING SOON



KENDAL Lighting (BC) Inc.

#110, 6780 Dennett Place Delta, B.C. V4G 1N4 Ph: (604) 952-5510 · Toll Free: 1-888-306-3267

info@kendallighting.com www.kendallighting.com