



Low Voltage Track Cylinder

Model No. TL7101-ORB

Project Details

| | |
|--------------|--|
| Job Name | |
| Location | |
| Type/Qty | |
| Contact Info | |
| Note | |

Features

- Directional light source providing 125° vertical aiming capability with 305° horizontal rotation
- Head length: 4", Dia.: 2.5"
- Dimmer compatible
- Suction cup lamp removal aid included
- Ceramic 12V AC MR16 base socket
- May be modified to fit other major brands
- I/P: AC 120V 60Hz 0.6A
- O/P: AC 12V 80W max. *
- * Our 80 watt rating is reserved for Trac-Tech low voltage cylinders built to the highest standards. Although rated for use with 50 watt bulbs, these heads feature top quality 80 watt electronic transformers to allow a longer, trouble-free life.

SPECIFICATION

| | |
|-----------------------------|------------|
| OAH (in.) | 8 |
| Overall Width (in.) | 2.5 |
| OA Depth (in.) | 4 |
| Bulb | MR16CG 12V |
| Max. wattage (W) | 50 |
| Number of Bulbs | 1 |
| Bulb included | No |
| Dimmable | Yes |
| Voltage | 12V |
| Certifications and Listings | ETL Listed |
| Warranty | 1 Year |

LED Info



Description

Low voltage track head cylinder in a Oil Rubbed Bronze finish for use with MR16CG 12V/50W Lamps

LINE DRAWING
CURRENTLY UNAVAILABLE



IMAGE COMING SOON



KENDAL Lighting (BC) Inc.

#110, 6780 Dennett Place Delta, B.C. V4G 1N4 Ph: (604) 952-5510 · Toll Free: 1-888-306-3267

info@kendallighting.com www.kendallighting.com